



## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>5</sup> : <b>H04J 13/00</b>	<b>A1</b>	(11) International Publication Number: <b>WO 92/10890</b> (43) International Publication Date: 25 June 1992 (25.06.92)
--	-----------	---

(21) International Application Number: PCT/US91/09295


(22) International Filing Date: 6 December 1991 (06.12.91)

(30) Priority data:  
624,118 7 December 1990 (07.12.90) US(71) Applicant: QUALCOMM INCORPORATED [US/US];  
10555 Sorrento Valley Road, San Diego, CA 92121 (US).(72) Inventors: GILHOUSEN, Klein, S.; 4039 Calgary Avenue,  
San Diego, CA 92122 (US). ANTONIO, Franklin, P.;  
2765 Cordoba Cove, Del Mar, CA 92014 (US).(74) Agent: MILLER, Russell, B.; Qualcomm Incorporated,  
10555 Sorrento Valley Road, San Diego, CA 92121 (US).

(81) Designated States: AT (European patent), AU, BE (European patent), BG, BR, CA, CH (European patent), CS, DE (European patent), DK (European patent), ES (European patent), FI, FR (European patent), GB (European patent), GR (European patent), HU, IT (European patent), JP, KP, KR, LU (European patent), MC (European patent), NL (European patent), NO, PL, RO, SE (European patent), SU\*.

**Published***With international search report.*

(54) Title: CDMA MICROCELLULAR TELEPHONE SYSTEM AND DISTRIBUTED ANTENNA SYSTEM THEREFOR



## (57) Abstract

A code division multiple access (CDMA) communication system in which cellular techniques are utilized in a wireless Private Branch Exchange (PBX) environment. A microcellular arrangement is defined in which a base station (10) communicates user information signals using CDMA communication signals with subscriber terminals. A distributed antenna system (26) is utilized in the system to provide multipath signals which facilitate signal diversity for enhanced system performance.

# + DESIGNATIONS OF "SU"

Any designation of "SU" has effect in the Russian Federation. It is not yet known whether any such designation has effect in other States of the former Soviet Union.

## FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	ES	Spain	MG	Madagascar
AU	Australia	FI	Finland	ML	Mali
BB	Barbados	FR	France	MN	Mongolia
BE	Belgium	GA	Gabon	MR	Mauritania
BF	Burkina Faso	GB	United Kingdom	MW	Malawi
BG	Bulgaria	GN	Guinea	NL	Netherlands
BJ	Benin	GR	Greece	NO	Norway
BR	Brazil	HU	Hungary	PL	Poland
CA	Canada	IT	Italy	RO	Romania
CF	Central African Republic	JP	Japan	SD	Sudan
CG	Congo	KP	Democratic People's Republic of Korea	SE	Sweden
CH	Switzerland	KR	Republic of Korea	SN	Senegal
CI	Côte d'Ivoire	LI	Liechtenstein	SU <sup>+</sup>	Soviet Union
CM	Cameroon	LK	Sri Lanka	TD	Chad
CS	Czechoslovakia	LU	Luxembourg	TG	Togo
DE	Germany	MC	Monaco	US	United States of America
DK	Denmark				

## CDMA MICROCELLULAR TELEPHONE SYSTEM AND DISTRIBUTED ANTENNA SYSTEM THEREFOR

### 5 BACKGROUND OF THE INVENTION

#### I. Field of the Invention

The present invention relates to wireless PBX and wireless local  
10 loop telephone systems. More specifically, the present invention relates to a novel and improved microcellular telephone system and distributed antenna system therefor so as to facilitate indoor communications using spread spectrum communication signals.

#### 15 II. Description of the Related Art

The use of code division multiple access (CDMA) modulation techniques is one of several techniques for facilitating communications in which a large number of system users are present. Other multiple  
20 access communication system techniques, such as time division multiple access (TDMA), frequency division multiple access (FDMA) and AM modulation schemes such as amplitude companded single sideband (ACSSB) are known in the art. However the spread spectrum modulation technique of CDMA has significant advantages over these  
25 modulation techniques for multiple access communication systems. The use of CDMA techniques in a multiple access communication system is disclosed in U.S. Patent No. 4,901,307, issued February 13, 1990, entitled "SPREAD SPECTRUM MULTIPLE ACCESS COMMUNICATION SYSTEM USING SATELLITE OR TERRESTRIAL  
30 REPEATERS", assigned to the assignee of the present invention, of which the disclosure thereof is incorporated by reference.

In the just mentioned patent, a multiple access technique is disclosed where a large number of mobile telephone system users each having a transceiver communicate through satellite repeaters or

terrestrial base stations (also referred to as cell-sites stations, cell-sites or for short, cells) using code division multiple access (CDMA) spread spectrum communication signals. In using CDMA communications, the frequency spectrum can be reused multiple times thus permitting an increase in system user capacity. The use of CDMA results in a much higher spectral efficiency than can be achieved using other multiple access techniques.

The terrestrial channel experiences signal fading that is characterized by Rayleigh fading. The Rayleigh fading characteristic in the terrestrial channel signal is caused by the signal being reflected from many different features of the physical environment. As a result, a signal arrives at a mobile unit receiver from many directions with different transmission delays. At the UHF frequency bands usually employed for mobile radio communications, including those of cellular mobile telephone systems, significant phase differences in signals traveling on different paths may occur. The possibility for destructive summation of the signals may result, with on occasion deep fades occurring.

Terrestrial channel fading is a very strong function of the physical position of the mobile unit. A small change in position of the mobile unit changes the physical delays of all the signal propagation paths, which further results in a different phase for each path. Thus, the motion of the mobile unit through the environment can result in a quite rapid fading process. For example, in the 850 MHz cellular radio frequency band, this fading can typically be as fast as one fade per second per mile per hour of vehicle speed. Fading this severe can be extremely disruptive to signals in the terrestrial channel resulting in poor communication quality. Additional transmitter power can be used to overcome the problem of fading. However, such power increases effect both the user, in excessive power consumption, and the system by increased interference.

The CDMA modulation techniques disclosed in U.S. Patent No. 4,901,307 offer many advantages over narrow band modulation

techniques used in communication systems employing satellite or terrestrial repeaters. The terrestrial channel poses special problems to any communication system particularly with respect to multipath signals. The use of CDMA techniques permit the special problems of the terrestrial channel to be overcome by mitigating the adverse effect of multipath, e.g. fading, while also exploiting the advantages thereof.

In a CDMA cellular telephone system, the same wide band frequency channel can be used for communication in all cells. The CDMA waveform properties that provide processing gain are also used to discriminate between signals that occupy the same frequency band. Furthermore the high speed pseudonoise (PN) modulation allows many different propagation paths to be separated, provided the difference in path delays exceed the PN chip duration, i.e.  $1/\text{bandwidth}$ . If a PN chip rate of approximately 1 MHz is employed in a CDMA system, the full spread spectrum processing gain, equal to the ratio of the spread bandwidth to system data rate, can be employed to discriminate against paths that differ by more than one microsecond in path delay from each other. A one microsecond path delay differential corresponds to differential path distance of approximately 1,000 feet. The urban environment typically provides differential path delays in excess of one microsecond, and up to 10-20 microseconds are reported in some areas.

In narrow band modulation systems such as the analog FM modulation employed by conventional telephone systems, the existence of multiple paths results in severe multipath fading. With wide band CDMA modulation, however, the different paths may be discriminated against in the demodulation process. This discrimination greatly reduces the severity of multipath fading. Multipath fading is not totally eliminated in using CDMA discrimination techniques because there will occasionally exist paths with delayed differentials of less than the PN chip duration for the particular system. Signals having path delays on this order cannot be discriminated against in the demodulator, resulting in some degree of fading.

It is therefore desirable in the CDMA cellular telephone system that some form of diversity be provided which would permit a system to reduce fading. Diversity is one approach for mitigating the deleterious effects of fading. Three major types of diversity exist: time diversity, frequency diversity and space diversity.

Time diversity can best be obtained by the use of repetition, time interleaving, and error detection and correction coding which is a form of repetition. The present invention employs each of these techniques as a form of time diversity.

CDMA by its inherent nature of being a wideband signal offers a form of frequency diversity by spreading the signal energy over a wide bandwidth. Therefore, frequency selective fading affects only a small part of the CDMA signal bandwidth.

Space or path diversity is obtained by providing multiple signal paths through simultaneous links from a mobile user through two or more cell-sites. Furthermore, path diversity may be obtained by exploiting the multipath environment through spread spectrum processing by allowing a signal arriving with different propagation delays to be received and processed separately. Examples of path diversity are illustrated in copending U.S. Patent Application entitled "SOFT HANDOFF IN A CDMA CELLULAR TELEPHONE SYSTEM", Serial No. 07/433,030, filed November 7, 1989, and copending U.S. Patent Application entitled "DIVERSITY RECEIVER IN A CDMA CELLULAR TELEPHONE SYSTEM", Serial No. 07/432,552, also filed November 7, 1989, both assigned to the assignee of the present invention.

The deleterious effects of fading can be further controlled to a certain extent in a CDMA system by controlling transmitter power. A system for cell-site and mobile unit power control is disclosed in copending U.S. Patent Application entitled "METHOD AND APPARATUS FOR CONTROLLING TRANSMISSION POWER IN A CDMA CELLULAR MOBILE TELEPHONE SYSTEM", Serial No. 07/433,031, filed November 7, 1989, also assigned to the assignee of the present invention.

The CDMA techniques as disclosed in U.S. Patent No. 4,901,307 contemplated the use of coherent modulation and demodulation for both directions of the link in mobile-satellite communications. Accordingly, disclosed therein is the use of a pilot carrier signal as a coherent phase reference for the satellite-to-mobile link and the cell-to-mobile link. In the terrestrial cellular environment, however, the severity of multipath fading, with the resulting phase disruption of the channel, precludes usage of coherent demodulation technique for the mobile-to-cell link. The present invention provides a means for overcoming the adverse effects of multipath in the mobile-to-cell link by using noncoherent modulation and demodulation techniques.

The CDMA techniques as disclosed in U.S. Patent No. 4,901,307 further contemplated the use of relatively long PN sequences with each user channel being assigned a different PN sequence. The cross-correlation between different PN sequences and the autocorrelation of a PN sequence for all time shifts other than zero both have a zero average value which allows the different user signals to be discriminated upon reception.

However, such PN signals are not orthogonal. Although the cross-correlations average to zero, for a short time interval such as an information bit time the cross-correlation follows a binomial distribution. As such, the signals interfere with each other much the same as if they were wide bandwidth Gaussian noise at the same power spectral density. Thus the other user signals, or mutual interference noise, ultimately limits the achievable capacity.

The existence of multipath can provide path diversity to a wideband PN CDMA system. If two or more paths are available with greater than one microsecond differential path delay, two or more PN receivers can be employed to separately receive these signals. Since these signals will typically exhibit independence in multipath fading, i.e., they usually do not fade together, the outputs of the two receivers can be diversity combined. Therefore a loss in performance only occurs when both receivers experience fades at the same time. Hence, one aspect of

the present invention is the provision of two or more PN receivers in combination with a diversity combiner. In order to exploit the existence of multipath signals, to overcome fading, it is necessary to utilize a waveform that permits path diversity combining operations to be performed.

5 A method and system for constructing PN sequences that provide orthogonality between the users so that mutual interference will be reduced is disclosed in copending U.S. Patent Application entitled "SYSTEM AND METHOD FOR GENERATING SIGNAL WAVEFORMS  
10 IN A CDMA CELLULAR MOBILE TELEPHONE SYSTEM", Serial No. 07/543,496, filed June 25, 1990, also assigned to the assignee of the present invention. Using these techniques in reducing mutual interference allowing higher system user capacity and better link performance. With orthogonal PN codes, the cross-correlation is zero over a predetermined  
15 time interval, resulting in no interference between the orthogonal codes, provided only that the code time frames are time aligned with each other.

In an such a CDMA cellular mobile system as disclosed in Serial No. 07/543,496, signals are communicated between a cell-site and mobile  
20 units using direct sequence spread spectrum communication signals. In the cell-to-mobile link, pilot, sync, paging and voice channels are defined. Information communicated on the cell-to-mobile link channels are, in general, encoded, interleaved, bi-phase shift key (BPSK) modulated with orthogonal covering of each BPSK symbol along with  
25 quadrature phase shift key (QPSK) spreading of the covered symbols. In the mobile-to-cell link, access and voice channels are defined. Information communicated on the mobile-to-cell link channels are, in general, encoded, interleaved, orthogonal signalling along with QPSK spreading. Using orthogonal PN sequences does in fact reduce mutual  
30 interference, thereby permitting greater user capacity, in addition to supporting path diversity so as to overcome fading.

The above mentioned patent and patent applications disclose a novel multiple access technique wherein a large number of mobile



telephone system users communicate through satellite repeaters or terrestrial base stations using code division multiple access spread spectrum modulation that allows the spectrum to be reused multiple times. The resulting system design has a much higher spectral efficiency than can be achieved using previous multiple access techniques.

In cellular telephone systems, a large geographic area is provided with mobile telephone service by installing a number of cell-sites situated so as to provide coverage of the entire geographic area. If service demand exceeds the capacity that can be provided by a set of cell-sites that just provides coverage, the cells are subdivided into smaller cells. This process has been carried out to the extent that some major metropolitan areas have nearly 200 cell-sites.

The technique described in U.S. Patent No. 4,901,307 uses CDMA to achieve a very high capacity by providing marginal isolation gain through the exploitation of system characteristics and functions such as multiple steerable antennas, speech activity and reuse of the entire frequency band in every cell of the system. The result is a significantly higher system capacity than provided by other multiple access techniques such as FDMA and TDMA.

In a further development of the cellular telephone idea, it is desired to provide a number of very small cells, called microcells, which would provide coverage of a very limited geographic area. Usually, it is considered that such areas are limited to a single floor of an office building and the mobile telephone service can be viewed as a cordless telephone system that may or may not be compatible with the mobile cellular telephone system. The rationale for providing such a service is similar to the reasoning for use of Private Branch Exchange (PBX) systems in business offices. Such systems provide for low cost phone service for a large number of calls between phones within the business while providing simplified dialing for internal phone numbers. A few lines are also provided to connect the PBX system to the public telephone system, allowing calls to be made and received between phones in the PBX system and telephones located elsewhere. It is desirable for the

microcell system to provide a similar level of service but with the added feature of cordless operation anywhere within the service area of the PBX.

5 In applications such as the wireless PBX or Wireless local loop telephone systems path delays are much shorter in duration than in cellular mobile systems. In buildings and other indoor environments where PBX systems are used it is necessary to provide a form of diversity which will enable discrimination between CDMA signals.

10 The primary problem solved by the disclosed invention is the provision of a simple antenna system that provides high capacity, simple installation, good coverage and excellent performance. Another problem is to achieve the above limited coverage while maintaining compatibility with the mobile cellular system and while taking a negligible amount of capacity away from the mobile system. This is  
15 achieved in the disclosed invention by combining the capacity properties of CDMA with a new distributed antenna design that confines the radiation to a very limited and carefully controlled area.

The implementation of spread spectrum communication techniques, particularly CDMA techniques, in a PBX environment  
20 therefore provides features which vastly enhance system reliability and capacity over other communication system techniques. CDMA techniques as previously mentioned further enable problems such as fading and interference to be readily overcome. Accordingly, CDMA techniques further promote greater frequency reuse, thus enabling a  
25 substantial increase in the number of system users.

## SUMMARY OF THE INVENTION

30 A key aspect in the wireless PBX and the wireless local loop of the present invention is the CDMA distributed antenna. In this concept, a set of simple antennas are fed by a common signal with only time delay processing to distinguish signals. The transmit output of the cell

- transmitter is fed down a coaxial cable to a string of radiators. The radiators are connected to the cable using power splitters. The resulting signals, amplified as necessary, are fed to the antennas. The salient features of this antenna concept are: (1) extremely simple and inexpensive; (2) neighboring antennas have time delays inserted in feed structure so signals received from two antennas are distinguishable by PN temporal processing; (3) exploits direct sequence CDMA's ability to discriminate against multipath; and (4) creates deliberate multipath that satisfies discrimination criteria.
- 10 In the distributed antenna processing, each antenna taps into the distribution cable somewhat like a cable TV system. Broadband gain is provided as needed at the antennas or at the cable taps. Note that the cable system will usually consist of two cables, one for transmit signals and one for receive signals. In many cases, the necessary delay will be provided naturally by the distribution cable and no additional delay elements will be necessary. When additional delay is necessary, it will usually prove simplest to coil up a length of coaxial cable.
- 15 A very important feature of this architecture is that no signal specific processing is necessary. In particular, no filtering, mixing translation or other complex signal processing operations need be performed. Only amplification is needed and that is provided "in bulk" to all of the signals in the cable with a single amplifier.
- 20 Another advantage is that little site specific engineering is required for installation. Normally, antenna placement will be determined only by physical constraints, together with the requirement that every location desiring service must be covered by at least one antenna. There is no concern for overlap. In fact, overlapping coverage is desirable in that it provides diversity operation to all terminals in the overlap area. Overlap is, however, not required.
- 25 The advantages of the distributed antenna concept become clear when considering the inherent simplicity of the cell equipment required to support a wireless PBX, wireless local loop or wireless home extension phone.
- 30

For the initial installation of a wireless PBX in a hotel or office building it is probable that a system capable of handling up to 40 simultaneous calls will be adequate. For a system of this capacity, only a single wideband (1.25 MHz bandwidth) receiver/transmitter needs to be  
5 provided. A single receiver/transmitter is then coupled into the antenna system drive cable. As described, this can be a single serial string of antenna elements.

Another possible antenna approach allows two or more cables to be driven in parallel by the receiver/transmitter with the necessary delay  
10 elements located with the receiver/transmitter equipment. As the capacity demand for a single system grows beyond 40 simultaneous calls, the system can be expanded in two different dimensions.

First, and simplest is the use of additional wideband frequency channels. In the cellular telephone application, the total 12.5 MHz  
15 bandwidth available for each direction for each carrier is subdivided into up to ten different 1.25 MHz wideband channels. For example, to double capacity to 80 simultaneous calls without changing the antenna system, a second receiver/transmitter unit would be added along with the necessary digital channel unit/vocoder equipment. If the entire  
20 spectrum of ten channels is not required for CDMA, then the remainder can be used by analog FM (or even digital TDMA) using the standard 30 kHz channelization.

If it is desired to increase capacity without using additional frequency spectrum then the antenna subsystem can be subdivided into  
25 "pseudo-sectors." In this architecture, the antenna drive cable is divided so as to provide two or more ports. Normally, you would try to have the antennas in each of the pseudo-sectors to be relatively disjoint from each other, although this is not critical. Each of the pseudo-sector is then provided with its own receiver/transmitter unit. The digitized sample  
30 bus output of the receiver/transmitters is fed to all of the channel units.

The channel units, as they are designed for cellular service, provide for up to three sector bus connections. In cellular service, this would allow three adjoining sectors of a cell to be connected to a channel

unit. The channel unit provides diversity combining of signals from all three sectors at the symbol level, thus providing a very high level of diversity combining. In the wireless PBX application, three antenna strings serving adjoining service areas could be connected to these three  
5 busses. This would allow a "soft handoff" without switch intervention to be accomplished between any of the antennas in the three antenna strings. This has the advantage of "hiding" the handoff process from the switch and allows the switch to be a generic PBX.

Clearly, the above architecture could be allowed to grow to great  
10 size. With ten wideband channels in use in three "pseudo-sectors", approximately 1200 simultaneous calls could be processed. This could be serving on the order of 15,000 lines corresponding to a large size central office capacity. Growth beyond this capacity is also possible but the switching architecture would, of necessity, begin to take on some of the  
15 characteristics and requirements of a cellular system.

The CDMA system described above for the Wireless PBX application can also be applied essentially unchanged to the wireless local loop problem. In wireless local loop applications it is desired to provide improved telephone service to a (generally) built up area with  
20 small cost and ease of installation of the necessary infrastructure. The wireless local loop equipment would be co-sited with the central office switch serving the area.

The vocoders, channel units and receiver/transmitters would all be located together at the same facility as the switch. The  
25 receiver/transmitter(s) would be coupled to the distributed antenna system as described above. In this system, the RF signals for both in-bound and out-bound signals pass through a pair of cables. The cables are tapped periodically to drive radiating elements. The cable taps may or may not require the use of amplification to maintain signal levels.

30 The home telephone unit for interface with the wireless local loop would consist of a low cost CDMA mobile phone modified for use with mains power and a simple fixed antenna. The telephone handset would plug into this RF unit. The simplicity of the user equipment would be

completely consistent with user installation. The customer would simply take it home, open the box, plug it in and begin to make calls.

The architecture of the system allows for a simple evolution as the market is penetrated. The service could begin with a single  
5 omnidirectional antenna located at the equipment site. This antenna would be mounted on a high tower so as to provide coverage of the area. Note that the first objective with initial service is universal coverage of the service area so that all customers desiring service may subscribe.

Then, as demand causes the need for additional capacity, the  
10 antennas could be sectorized. As demand grows still greater, the most dense sectors can be replaced with the distributed antenna. The distributed antenna will allow higher capacity because interference from adjacent cells is reduced and because subscriber units may operate a lower power and generate less interference to neighboring cells.

15 Mobile service can also be provided by this system if provision is made for appropriate connections between adjacent central offices for handoff if the user moves from one central office's service area to another. This handoff can be made soft in the manner provided by the CDMA cellular system with the use of the appropriate software and  
20 hardware between the central office switches.

## BRIEF DESCRIPTION OF THE DRAWINGS

The features, objects, and advantages of the present invention will  
25 become more apparent from the detailed description set forth below when taken in conjunction with the drawings:

Figure 1 is a schematic overview of an exemplary CDMA wireless PBX telephone system;

Figure 2 is an illustration of an exemplary antenna pattern for an  
30 distributed antenna system of Figure 1;

Figure 3 is a schematic diagram of an alternative distributed antenna system for use with the system of Figure 1;

Figure 4 is a block diagram of the exemplary microcell equipment as implemented in a CDMA wireless PBX telephone system; and

Figure 5 is a block diagram of the mobile unit telephone configured for CDMA communications in the CDMA wireless PBX telephone system.

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10 In a CDMA wireless telephone system, a microcell has a controller, a plurality of spread spectrum modulator-demodulator units, which are also referred to as channel unit or modems, a transceiver and a distributed antenna system. Each channel unit consists of a digital spread spectrum transmit modulator, a digital spread spectrum data  
15 receiver and a searcher receiver. Each modem at the microcell is assigned to a mobile unit as needed to facilitate communications with the assigned mobile unit. The term "mobile unit" or subscriber terminal as used with reference to the microcellular system is generally a CDMA telephone set that is configured as a hand-held personal  
20 communications device, a portable CDMA telephone or even a CDMA telephone that is fixed at a specific location.

In the CDMA wireless PBX or local loop telephone system, the microcell transmits a "pilot carrier" signal. The pilot signal is used by the mobile units to obtain initial system synchronization and to provide  
25 robust time, frequency and phase tracking of the microcell transmitted signals. Each microcell also transmits spread spectrum modulated information, such as microcell identification, system timing, mobile paging information and various other control signals.

Upon acquisition of the pilot signal, i.e. initial synchronization of  
30 the mobile unit with the pilot signal, the mobile unit searches for another carrier intended to be received by all system users in the cell. This carrier, called the synchronization channel, transmits a broadcast message containing system information for use by the mobiles in the

system. The system information identifies the microcell and the system in addition to conveying information which allows the long PN codes, interleaver frames, vocoders and other system timing information used by the mobile mobile unit to be synchronized without additional  
5 searching. Another channel, called the paging channel may also be provided to transmit messages to mobile units indicating that a call has arrived for them, and to respond with channel assignments when a mobile initiates a call.

When a call is initiated, a pseudonoise (PN) code address is  
10 determined for use during the course of this call. The code address may be either assigned by the microcell or be determined by prearrangement based upon the identity of the mobile unit.

In Figure 1, wireless base station 10 is illustrated which includes PBX switch 12 and microcell 14. PBX switch 12 is used in interfacing base  
15 station 10 to the public switched telephone network (PSTN) and/or PBX system wired telephones. PBX switch 12 serves in routing telephone calls to/from microcell 14 which communicates the calls via CDMA communication signals with the appropriate mobile unit. Microcell 14 includes CDMA controller 18, a plurality of channel units 20A - 20N and  
20 corresponding vocoders 22A - 22N, transceiver 24 and distributed antenna system 26.

PBX switch 12 couples calls to and from a particular available vocoder - channel unit pair. PBX switch 12 is preferably a device which is capable of providing control in transfer of signals therefrom to various  
25 vocoders. PBX switch 12 may be a digital device which provides analog or digital voice signal, in addition to digital data signals on a common bus, via well known techniques such as a time multiplexed format, to and from the various vocoders. Voice calls received from PBX switch 12 are digitally encoded, if not previously digitized, by a vocoder of a  
30 selected vocoder - channel unit pair, such as vocoder 22A of the vocoder - channel unit pair comprised of vocoder 22A and channel unit 20A. The selected vocoder places the voice in a format which is preferred for CDMA encoding and transmission. Further details on the



vocoder is discussed later herein. The channel unit of the selected vocoder - channel unit pair, provides CDMA encoding, and other encoding, of the digitally encoded voice signal to be transmitted to a mobile unit. It should be understood that digitized data may also be transmitted through PBX switch 12 which although are not digitized are formatted for transfer for CDMA encoding and transmission. The vocoder and channel unit are discussed in further detail later herein.

The CDMA encoded signal is output from the respective channel unit to transceiver 24 for frequency conversion to the appropriate transmission frequency and power controlled in transmission. The RF signal is provided to an antenna system 26 which is in the form of a distributed antennas 28A - 28I with delay elements 30A - 30J disposed between adjacent antennas. Antennas 28A - 28I may be generally configured as omnidirectional antennas or directional antennas have a specific pattern. Delay elements 30A - 30J may be simple delay lines such as lengths of coaxial cabling, or other well known active or passive delay elements, capable of providing a one microsecond (1  $\mu$ sec) delay itself or in combination with the interconnection cabling. It should be understood that other means such as optical fibers may be used as the transmission lines between transceiver 24 and antenna system 26. Furthermore, such means may also be used between antenna themselves, and with optical delay devices and proper RF-Optic interfacing with the antennas.

Figure 2 provides an illustration of an exemplary antenna pattern for a series of antennas configured in accordance with the present invention. The antenna pattern as illustrated in Figure 2 is generated by a series of omnidirectional antennas each defining a separate antenna pattern 40A - 40I that is preferably overlapping with the pattern of an adjacent antenna. The overlapping of patterns provides continuous antenna coverage for the desired area. The antennas are coupled in series in an exemplary manner such as indicated by line 42.

It should be understood that the antennas may be designed to be positioned such that their patterns are substantially or completely

overlapping in area of coverage. In such an arrangement a delay is provided in the antennal feeds to provide a time diversity in signals. Such an arrangement creates a multipath environment wherein diversity is provided for signal discrimination purposes. This technique  
5 is applicable to the microcell environment where additional multipath is desirable. However such a technique is particularly applicable to the CDMA cellular mobile telephone environment where multipath signals are not inherently produced by the terrain. Such is the case in flat open areas where signal reflections, and hence multipath, are at a minimum.  
10 Utilization of this technique provides antenna diversity in the cell-to-mobile link with a single antenna.

It should also be understood that various modifications to the antenna system of Figure 1 may be constructed. For example, it is envisioned that parallel strings of serially connected antennas with a  
15 feed from a common source may be utilized. In such an arrangement delay elements would be used as necessary in the feed lines. These delay elements would provide a delay between signals as radiated from the antennas such that the same signal is radiated from a different antenna at a different time.

20 Figure 3 illustrates an alternate embodiment of antenna system 26 for the wireless PBX system of Figure 1. In Figure 3 antenna system 26' is comprised of central or local antenna 50 coupled to transceiver 26 in place of antennas 28A - 28I and delay elements 30A - 30J. A series of remote antenna systems 52A - 52I are remotely located from antenna 50.  
25 Each of remote antenna systems 52A - 52I is comprised of a high gain antenna 54A - 54I, delay element 56A - 56I, and remote antenna 58A - 58I. In this embodiment the distribution of signals within the antenna system is accomplished without the use of cabling.

In antenna system 26' signals from transceiver 24 are radiated by  
30 local antenna 50 to each of high gain antennas 54A - 54I, typically a directional antenna, where it is amplified as received. The amplified signal is then delayed by a predetermined amount, typically greater than one microsecond, by a corresponding delay element 56A - 56I. The delay

period of each of delay elements 56A - 56I is different from one another typically by a multiple of the one microsecond delay period. The signal is output from each delay element to a corresponding remote antenna 58A - 58I where the signal is re-radiated.

5           Conversely, signals transmitted by a mobile unit are received by one or more of remote antenna 58A - 58I where input to a corresponding delay element 56A - 56I. Delay element 56A - 56I again provide a predetermined delay in the received signal with the delayed signal provided to a corresponding one of high gain antennas 54A - 54I. High  
10 gain antennas 54A - 54I amplify and radiate the signal to local antenna 50.

          The antenna system of the present invention is unique to the application microcellular system herein. As mentioned previously, control of signal power is an important aspect of a CDMA telephone  
15 system in order to realize increases in user capacity. A conventional omnidirectional antenna radiates a signal roughly equally in all directions. The signal strength is reduced with radial distance from the antenna according to the propagation characteristics of the physical environment. The propagation law may vary from inverse square law  
20 to inverse 5.5 power law of the radial distance.

          A cell that is designed to serve a certain radius must transmit at a sufficient power level so that a mobile unit at the edge of the cell will receive an adequate signal power level. Mobile units that are closer than the edge of the cell will receive a greater than adequate signal power  
25 level. Directional antennas beams can be formed using a variety of techniques known in the art. However, the forming of directional beams cannot alter the propagation law. Coverage of a desired area by a radio signal can be obtained by a combination of antenna pattern, antenna placement and transmitter power.

30           The use of a distributed antenna system provides the desired antenna pattern, such as coverage of a hallway of a building, where each antenna element provides limited coverage. In providing limited antenna coverage the power necessary to reach a mobile unit within the

smaller coverage area is correspondingly reduced since propagation loss is reduced.

However, there is a problem with multiple antennas all radiating the same signal. There will be areas, particularly near points equidistant from two or more of the antennas where the signals may be received from the two antennas that cancel each other. Points where the signal may cancel are separated by approximately one-half wavelength. At 850 MHz this is equal to 17.6 cm or about 7 inches. If two signals arrive at the receive antenna at equal strength but opposite in phase, then they may so cancel. Essentially, this is man-made multipath fading. As with natural multipath fading, diversity is the best method for mitigation of fading. The CDMA system design provides several methods of diversity for mitigation of multipath fading.

The above mentioned copending patent applications disclose a cellular telephone system that uses a CDMA modulation with a 1.25 MHz bandwidth, multiple forms of diversity, and very careful transmitter power control. One method of diversity is the provision of a "rake" receiver architecture in which multiple receivers are provided, each capable of receiving a signal that has traveled a different path and therefore exhibits a different delay. Included is a separate searcher receiver which continuously scans the time domain looking for the best paths and assigning the multiple receivers accordingly.

Another method of diversity is path diversity. In path diversity, the signal is radiated from multiple antennas located in different places, possibly providing more than one propagation path. If two or more antennas can provide acceptable communication paths to the mobile receiver then path diversity fading mitigation can be obtained.

In the microcell system it is desired to provide multiple antennas in order to provide coverage in a desired coverage area but the capacity demand for the system does not require that each antenna be supplied with a separate set of signals as in the conventional cellular system. Instead, to minimize the cost, it is desired to feed some or all of the antennas in the microcell system with the same RF signals. In areas of

the microcell system where good paths are possible to two or more of the antennas then path diversity can be obtained.

The problem with feeding the antennas of the microcell system with identically the same signals is that phase cancellation can result in  
5 places where near equal signals are received from two or more antennas. What is desired is a simple, low cost way to distinguish the signals feeding the different antennas without adding significantly to the cost of the system. The method for so doing in the present invention is the addition of delay elements in the feeder lines between the base station  
10 transceiver and the antennas.

If the multiple antenna system described above is provided with delay lines in the feeders such that each antenna is driven by a signal one or more microseconds delayed from its neighbors, then the multiple receiver architecture of the mobiles will allow the signal from each  
15 antenna to be received separately and to be coherently combined in such a way that cancellation will not occur. In fact, fading due to other reflections in the environment can be greatly mitigated by the disclosed technique because a form of path diversity is provided.

A microcell is configured as a standard CDMA cell-site as described  
20 in the above mentioned patent applications. In addition to the functions disclosed in these applications, the system includes an antenna system with multiple radiators installed throughout the area to be covered by the microcell. The signals are distributed to the radiators by coaxial cables or other means. A one or more microsecond delay line is  
25 included in series with the cable connecting two adjacent antennas.

The mobile units or terminals contain one or more CDMA receivers and a searcher receiver. The searcher scans the time domain determining what paths exist and which are the strongest paths. The available CDMA receivers are then assigned to the strongest available  
30 paths. The cell-site receivers contain a similar capability.

In the embodiment as illustrated in Figure 3, the radiators are not actually connected by cable but, rather, pick up the signal from another radiator using a high gain antenna. The signal picked up, amplified by a

small amount, delayed by a predetermined amount, and then re-radiated.

The CDMA system described in the aforementioned disclosures can provide a capacity equal to approximately 40 simultaneous calls in each cell of the system in each 1.25 MHz bandwidth CDMA channel. The resulting cell in the herein disclosed invention is the coverage area of the sum of the antenna patterns of each of the antennas connected by the common feeder system. Thus, the 40 call capacity is available anywhere within the coverage area. As mobile users move about in the system, all callers will continue to receive service no matter how they may congregate within the cell. This is especially useful in wireless PBX systems for businesses such as hotels which contain large ballrooms and other public spaces which could contain a large number of the system users at some times but not at other times during the business day. At other times, the users might all be located in their individual hotel rooms. It is highly desirable for a wireless PBX system to accommodate such situations.

With respect to cellular telephone systems, the Federal Communications Commission (FCC) has allocated a total of 25 MHz for mobile-to-cell links and 25 MHz for cell-to-mobile links. The FCC has divided the allocation equally between two service providers, one of which is the wireline telephone company for the service area and the other chosen by lottery. Because of the order in which allocations were made, the 12.5 MHz allocated to each carrier for each direction of the link is further subdivided into two sub-bands. For the wireline carriers, the sub-bands are each 10 MHz and 2.5 MHz wide. For the non-wireline carriers, the sub-bands are each 11 MHz and 1.5 MHz wide. Thus, a signal bandwidth of less than 1.5 MHz could be fit into any of the sub-bands, while a bandwidth of less than 2.5 MHz could be fit into all but one sub-band. Such a frequency scheme is also applicable to the microcellular system, however other frequency plans may be available and more desirable in certain instances.

To preserve maximum flexibility in allocating the CDMA technique to the available cellular frequency spectrum such as used in a cellular telephone system, the waveform should be less than 1.5 MHz in bandwidth. A good second choice would be a bandwidth of about  
5 2.5 MHz, allowing full flexibility to the wireline cellular carriers and nearly full flexibility to non-wireline cellular carriers. While using a wider bandwidth has the advantage of offering increased multipath discrimination, disadvantages exist in the form of higher equipment costs and lower flexibility in frequency assignment within the allocated  
10 bandwidth.

In a spread spectrum wireless PBX or local loop telephone system, such as disclosed herein, the preferred waveform design involves a direct sequence pseudonoise spread spectrum carrier as in the cellular telephone system as disclosed in the previously mentioned copending  
15 patent application and U.S. Patent No. 4,901,307. The chip rate of the PN sequence is chosen to be 1.2288 MHz such that the resulting bandwidth, about 1.25 MHz after filtering, is approximately one-tenth of the total bandwidth allocated to one cellular service carrier.

Another consideration in the choice of the exact chip rate is that it  
20 is desirable that the chip rate be exactly divisible by the baseband data rates to be used in the system. It is also desirable for the divisor to be a power of two. With a baseband data rate of 9600 bits per second, the PN chip rate is chosen to be 1.2288 MHz, i.e. 128 times 9600.

In the microcell-to-mobile link, the binary sequences used for  
25 spreading the spectrum are constructed from two different types of sequences, each with different properties to provide different functions. An outer code is shared by all signals in a microcell to provided discrimination between multipath signals. The outer code may also used to discriminate between signals transmitted to the mobile units by  
30 different microcells, should additional microcells exist in the system. There is also an inner code that is used to discriminate between user signals transmitted by single sector or cell.

The carrier waveform design in the preferred embodiment for the microcell transmitted signals utilizes a sinusoidal carrier that is quadrature phase (four phase) modulated by a pair of binary PN sequences that provide the outer code transmitted by a single sector or cell. The sequences are generated by two different PN generators of the same sequence length. One sequence bi-phase modulates the in-phase channel (I Channel) of the carrier and the other sequence bi-phase modulates the quadrature phase (Q Channel) of the carrier. The resulting signals are summed to form a composite four-phase carrier.

Although the values of a logical "zero" and a logical "one" are conventionally used to represent the binary sequences, the signal voltages used in the modulation process are +V volts for a logical "one" and -V volts for a logical "zero". To bi-phase modulate a sinusoidal signal, a zero volt average value sinusoid is multiplied by the +V or -V voltage level as controlled by the binary sequences using a multiplier circuit. The resulting signal may then be band limited by passing through a bandpass filter. It is also known in the art to lowpass filter the binary sequence stream prior to multiplying by the sinusoidal signal, thereby interchanging the order of the operations. A quadrature phase modulator consists of two bi-phase modulators each driven by a different sequence and with the sinusoidal signals used in the bi-phase modulators having a 90° phase shift therebetween.

In such an embodiment, the sequence length for the transmitted signal carrier is chosen to be 32768 chips. Sequences of this length can be generated by a modified maximal length linear sequence generator by adding a zero bit to a length 32767 chip sequence. The resulting sequence has good cross-correlation and autocorrelation properties.

A sequence this short in length is desirable in order to minimize acquisition time of the mobile units when they first enter the system without knowledge of system timing. With unknown timing, the entire length of the sequence must be searched to determine the correct timing. The longer the sequence, the longer time the acquisition search will require. Although sequences shorter than 32768 could be used, it must



be understood that as sequence length is reduced, the code processing gain is reduced. As processing gain is reduced, the rejection of multipath interference along with interference from adjacent cells and other sources will also be reduced, perhaps to unacceptable levels. Thus, there is a desire to use the longest sequence that can be acquired in a reasonable time. It is also desirable to use the same code polynomials in all cells so that the mobile unit, not knowing what cell it is in when initially acquiring synchronization, can obtain full synchronization by searching a single code polynomial.

All signals transmitted by a microcell share the same outer PN codes for the I and Q channels. The signals are also spread with an inner orthogonal code generated by using Walsh functions. A signal addressed to a particular user is multiplied by the outer PN sequences and by a particular Walsh sequence, or sequence of Walsh sequences, assigned by the system controller for the duration of the user's telephone call. The same inner code is applied to both the I and Q channels resulting in a modulation which is effectively bi-phase for the inner code.

It is well known in the art that a set of  $n$  orthogonal binary sequences, each of length  $n$ , for  $n$  any power of 2 can be constructed, see Digital Communications with Space Applications, S.W. Golomb et al., Prentice-Hall, Inc, 1964, pp. 45-64. In fact, orthogonal binary sequence sets are also known for most lengths which are multiples of four and less than two hundred. One class of such sequences that is easy to generate is called the Walsh function, also known as Hadamard matrices. A Walsh sequence is one of the rows of a Walsh function matrix. A Walsh function of order  $n$  contains  $n$  sequences, each of length  $n$  bits.

A Walsh function of order  $n$  (as well as other orthogonal functions) has the property that over the interval of  $n$  code symbols, the cross-correlation between all the different sequences within the set is zero, provided that the sequences are time aligned with each other. This can be seen by noting that every sequence differs from every other sequence in exactly half of its bits. It should also be noted that there is

always one sequence containing all zeroes and that all the other sequences contain half ones and half zeroes.

Since all the signals transmitted by a microcell are orthogonal to each other they do not contribute interference to each other. This eliminates the majority of the interference in most locations, allowing a higher capacity to be obtained.

As an added feature, the system may further use a voice channel which is a variable rate channel whose data rate can be varied from data block to data block with a minimum of overhead required to control the data rate in use. The use of variable data rates reduces mutual interference by eliminating unnecessary transmissions when there is no useful speech to be transmitted. Algorithms are utilized within the vocoders for generating a varying number of bits in each vocoder block in accordance with variations in speech activity. During active speech, the vocoder may produce 20 msec. data blocks containing 20, 40, 80, or 160 bits, depending on the activity of the speaker. It is desired to transmit the data blocks in a fixed amount of time by varying the rate of transmission. It is further desirable not to require signalling bits to inform the receiver how many bits are being transmitted.

The blocks are further encoded by the use of a cyclic redundancy check code (CRCC) which appends to the block an additional set of parity bits which can be used to determine whether or not the block of data has been decoded correctly. CRCC check codes are produced by dividing the data block by a predetermined binary polynomial. The CRCC consists of all or a portion of the remainder bits of the division process. The CRCC is checked in the receiver by reproducing the same remainder and checking to see if the received remainder bits are the same as the regenerated check bits.

In the disclosed invention, the receiving decoder decodes the block as if it contains 160 bits, and then again as if it contains 80 bits, etc. until all possible block lengths have been tried. The CRCC is computed for each trial decoding. If one of the trial decodings results in a correct CRCC, the data block is accepted and passed on to the vocoder for further

processing. If no trial decoding produces a valid CRCC, the received symbols are passed on to the system's signal processor where other processing operations can optionally be performed.

- 5 In the microcell transmitter, the power of the transmitted waveform is varied as the data rate of the block is varied. The highest data rate uses the highest carrier power. When the data rate is lower than the maximum, the modulator, in addition to lowering the power, repeats each encoded data symbol a number of times as required to achieve the desired transmission rate. For example, at the lowest  
10 transmission rate, each encoded symbol is repeated four times.

- In the mobile transmitter, the peak power is held constant but the transmitter is gated off  $1/2$ , or  $1/4$  or  $1/8$  of the time in accordance with the number of bits to be transmitted in the data block. The positions of the on-times of the transmitter is varied pseudo-randomly in accordance  
15 with the mobile user's addressed user code.

- As disclosed in copending application Serial No. 07/543,496 for the Cell-to-Mobile Link, i.e. Microcell-to-Mobile Link as used in the context herein, the Walsh function size  $n$ , is set equal to sixty-four ( $n = 64$ ) for the cell-to-mobile link. Therefore each of up to sixty-four different  
20 signals to be transmitted are assigned a unique orthogonal sequence. The forward error correction (FEC) encoded symbol stream for each voice conversation is multiplied by its assigned Walsh sequence. The Walsh coded/FEC encoded symbol stream for each voice channel is then multiplied by the outer PN coded waveform. The resultant spread  
25 symbol streams are then added together to form a composite waveform.

- The resulting composite waveform is then modulated onto a sinusoidal carrier, bandpass filtered, translated to the desired operating frequency, amplified and radiated by the antenna system. Alternate embodiments of the present invention may interchange the order of  
30 some of the just described operations for forming the cell-site transmitted signal. For example, it may be preferred to multiply each voice channel by the outer PN coded waveform and perform the filtering operation prior to summation of all the channel signals to be

radiated by the antenna. It is well known in the art that the order of linear operations may be interchanged to obtain various implementation advantages and different designs.

5 The waveform design for the wireless PBX service uses the pilot carrier approach for the microcell-to-mobile link as described in U.S. Patent No. 4,901,307. The pilot waveform uses the all-zero Walsh sequence, i.e. a Walsh sequence comprised of all zeroes that is found in all Walsh function sets. The use of the all-zero Walsh sequence for all  
10 cells' pilot carriers allows the initial search for the pilot waveform to ignore the Walsh functions until after the outer code PN synchronization has been obtained. The Walsh framing is locked to the PN code cycle by virtue of the length of the Walsh frame being a factor of the PN sequence length. Therefore, provided that the cell addressing offsets of the PN code are multiples of sixty-four chips (or the Walsh  
15 frame length) then the Walsh framing is known implicitly from the outer PN code timing cycle.

The pilot carrier is transmitted at a higher power level than a typical voice carrier so as to provide greater signal to noise and interference margin for this signal. The higher power level pilot carrier  
20 enables the initial acquisition search to be done at high speed and to make possible a very accurate tracking of the carrier phase of the pilot carrier by a relatively wide bandwidth phase tracking circuit. The carrier phase obtained from tracking the pilot carrier is used as the carrier phase reference for demodulation of the carriers modulated by user  
25 information signals. This technique allows many user carriers to share the common pilot signal for carrier phase reference. For example, in a system transmitting a total of fifteen simultaneous voice carriers, the pilot carrier might be allocated a transmit power equal to four voice carriers.

30 In addition to the pilot carrier, another carrier intended to be received by all system users in the microcell is transmitted by the microcell. This carrier, called the synchronization channel, also uses the same 32768 length PN sequence for spectrum spreading but with a

different, pre-assigned Walsh sequence. The synchronization channel transmits a broadcast message containing system information for use by the mobiles in the system. The system information identifies the cell-site and the system and conveys information allowing the long PN codes  
5 used for mobile information signals to be synchronized without additional searching. Another channel, called the paging channel may be provided to transmit messages to mobile units indicating that a call has arrived for them, and to respond with channel assignments when a mobile unit initiates a call.

10 Each voice carrier transmits a digital representation of the speech for a telephone call. The analog speech waveform is digitized using standard digital telephone techniques and then compressed using a vocoding process to a data rate of approximately 9600 bits per second. This data signal is then rate  $r = 1/2$ , constraint length  $K = 9$   
15 convolutional encoded, with repetition, and interleaved in order to provide error detection and correction functions which allow the system to operate at a much lower signal-to-noise and interference ratio. Techniques for convolutional encoding, repetition and interleaving are well known in the art.

20 The resulting encoded symbols are multiplied by an assigned Walsh sequence and then multiplied by the outer PN code. This process results in a PN sequence rate of 1.2288 MHz or 128 times the 9600 bps data rate. The resulting signal is then modulated onto an RF carrier and summed with the pilot and setup carriers, along with the other voice  
25 carriers. Summation may be accomplished at several different points in the processing such as at the IF frequency, or at the baseband frequency either before or after multiplication by the PN sequence.

Each voice carrier is also multiplied by a value that sets its transmitted power relative to the power of the other voice carriers. This  
30 power control feature allows power to be allocated to those links that require higher power due to the intended recipient being in a relatively unfavorable location. Means are provided for the mobiles to report their received signal-to-noise ratio to allow the power to be set at a level so as

to provide adequate performance without waste. The orthogonality property of the Walsh functions is not disturbed by using different power levels for the the different voice carriers provided that time alignment is maintained.

5        Figure 4 illustrates in block diagram form the exemplary embodiment microcell equipment of Figure 1. Common to both of the receiver and transceiver portions of transceiver 24 is diplexer 100. In Figure 4, the receiver system of transceiver 24 of microcell 14 is comprised of analog receiver 102, while the corresponding components  
10 of the channel unit, here channel unit 20A, is comprised of searcher receiver 104, digital data receiver 106 and decoder circuitry 108. The receiver system may also include an optional digital data receiver receiver 110. Further details of an exemplary embodiment of analog receiver 100 are provided in copending application Serial No. 07/543,496.

15        Microcell 14, as mentioned previously, includes CDMA controller 18 which is coupled to data receivers 106 and 110 along with searcher receiver 104. CDMA controller 18 provides among other functions, as Walsh sequence and code assignment, signal processing, timing signal generation, power control and various other related functions.

20        Signals received on antenna 26 are provided via diplexer 100 to analog receiver 100 and then to searcher receiver 104. Searcher receiver 104 is used to at the microcell to scan the time domain about the received signal to ensure that digital data receiver 106 is tracking and processing the strongest available time domain signal. Searcher receiver 104  
25 provides a signal to CDMA controller 18 which provides control signals to digital data receiver 106 for selecting the appropriate received signal for processing.

      The signal processing in the microcell data receiver and searcher receiver is different in several aspects than the signal processing by  
30 similar elements in the mobile unit. In the inbound, i.e. reverse or mobile-to-microcell link, the mobile unit does not transmit a pilot signal that can be used for coherent reference purposes in signal processing at the cell-site. The mobile-to-microcell link is characterized by a

non-coherent modulation and demodulation scheme using 64-ary orthogonal signalling.

In the 64-ary orthogonal signalling process, the mobile unit transmitted symbols are encoded into one of  $2^6$ , i.e. 64, different binary sequences. The set of sequences chosen are known as Walsh functions.  
5 The optimum receive function for the Walsh function m-ary signal encoding is the Fast Hadamard Transform (FHT).

Referring again to Figure 2, searcher receiver 104 and digital data 104, receive the signals output from analog receiver 102. In order to  
10 decode the spread spectrum signals transmitted to the particular cell-site receiver through which the mobile unit communicates, the proper PN sequences must be generated. Further details on the generation of the mobile unit signals are in pending application Serial No. 07/543,496.

The Viterbi decoder contained within circuitry 108 is of a type  
15 capable of decoding data encoded at the mobile unit with a constraint length  $K = 9$ , and of a code rate  $r = 1/3$ . The Viterbi decoder is utilized to determine the most likely information bit sequence. Periodically, nominally 1.25 msec, a signal quality estimate is obtained and transmitted as a mobile unit power adjustment command along with  
20 data to the mobile unit. This quality estimate is the average signal-to-noise ratio over the 1.25 msec interval.

Each data receiver tracks the timing of the received signal it is receiving. This is accomplished by the well known technique of correlating the received signal by a slightly early local reference PN  
25 and correlating the received signal with a slightly late local reference PN. The difference between these two correlations will average to zero if there is no timing error. Conversely, if there is a timing error, then this difference will indicate the magnitude and sign of the error and the receiver's timing is adjusted accordingly.

30 Signals from the PBX are coupled to the appropriate transmit modulator vocoder 22A - 22N under control of CDMA controller 18. For the example illustrated in Figure 4, vocoder 22A is used. Channel unit 20A further comprises transmit modulator 112 which under control of

CDMA controller 18 spread spectrum modulates the data for transmission to the intended recipient mobile unit.

The output of transmit modulator 112 is provided to transmit power control circuitry 114 where under the control of CDMA controller 18 the transmission power may be controlled. The output of circuitry 114 is provided to summer 116 where it is summed with the output of transmit modulator/transmit power control circuits of other channel units. Summer may be grouped with one of the channel units or considered as part of the transmitter portion of transceiver 24. The output of summer 116 is provided to the transmitter portion of transceiver 24 which is comprised of transmit power amplifier circuitry 118. Transmit power amplifier circuitry 118 amplifies the signal for output via diplexer 100 to antenna 26 for radiating to the mobile units within the microcell service area. Further details on exemplary transmitter circuitry of Figure 4 are illustrated in copending application Serial No. 07/543,496

Figure 4 further illustrates pilot/control channel generators and transmit power control circuitry 120 which may be contained with one of the channel units or as a separate component of the system. Circuitry 120 under control of CDMA controller 18 generates and power controls the pilot signal, the sync channel, and the paging channel for coupling to transmit power amplifier circuitry 118 for output via diplexer 100 to antenna 26.

In the preferred embodiment, Walsh function encoding of the channel signals is employed as the inner code. In the exemplary numerology as disclosed herein, a total of 64 different Walsh sequences are available with three of these sequences dedicated to the pilot, sync and paging channel functions. In the sync, paging and voice channels, input data is convolutionally encoded and then interleaved as is well known in the art. Furthermore, the convolutional encoded data is also provided with repetition before interleaving as is also well known in the art.



The pilot channel contains no data modulation and is characterized as an unmodulated spread spectrum signal that all of the users of a particular cell-site or sector use for acquisition or tracking purposes. Each cell, or if divided into sectors, each sector has a unique pilot signal. However, rather than using different PN generators for the pilot signals, it is realized that a more efficient way to generate different pilot signals is to use shifts in the same basic sequence. Utilizing this technique a mobile unit sequentially searches the whole sequence and tunes to the offset or shift that produces the strongest correlation. In using this shift of the basic sequence, the shifts must be such that the pilots in adjacent cells or sectors must not interfere or cancel.

The pilot sequence must therefore be long enough that many different sequences can be generated by shifts in the basic sequence to support a large number of pilot signals in the system. Furthermore, the separation or shifts must be great enough to ensure that there is no interference in pilot signals. Accordingly, in a exemplary embodiment of the present invention the pilot sequence length is chosen to be  $2^{15}$ . The sequence is generated started by a sequence  $2^{15}-1$  with an extra 0 appended to the sequence when a particular state is detected. In the exemplary embodiment there are chosen to be 512 different pilot signals with offsets in the basic sequence of 64 chips. However, offsets may be integer multiples of the 64 chip offset with a corresponding reduction in the number of different pilot signals.

In generating the pilot signal, the Walsh "zero" ( $W_0$ ) sequence which consists of all zeroes is used so as to not modulate the pilot signal, which in essence is the  $PN_I$  and  $PN_Q$  sequences. The Walsh "zero" ( $W_0$ ) sequence is therefore multiplied by the  $PN_I$  and  $PN_Q$  sequences in exclusive-OR gates. The resulting pilot signal thus contains only the  $PN_I$  and  $PN_Q$  sequences. With all cell-sites and sectors having the same PN sequence for the pilot signal, the distinguishing feature between cell-sites or sectors of origination of the transmission is the phase of the sequence.

The sync channel information is encoded and then multiplied in exclusive-OR gates by a preassigned Walsh sequence. In the exemplary

embodiment, the selected Walsh function is the ( $W_{32}$ ) sequence which consists of a sequence of 32 "ones" followed by 32 "zeros". The resulting sequence is then multiplied by the  $PN_I$  and  $PN_Q$  sequences in exclusive-OR gates.

5 In an exemplary embodiment the sync channel data information is provided to the transmit modulator typically at a rate of 1200 bps. In the exemplary embodiment the sync channel data is preferably convolutionally encoded at a rate  $r = 1/2$  with a constraint length  $K = 9$ , with each code symbol repeated twice. This encoding rate and constraint  
10 length is common to all encoded forward link channels, i.e. sync, paging and voice. In an exemplary embodiment, a shift register structure is employed for the generators of the code  $G_1 = 753$  (octal) and  $G_2 = 561$  (octal). The symbol rate to the sync channel is in the exemplary embodiment 4800 sps, i.e. one symbol is 208  $\mu\text{sec}$  or 256 PN chips.

15 The code symbols are interleaved by means of a convolutional interleaver spanning in the exemplary embodiment 40 msec. The tentative parameters of the interleaver are  $I = 16$  and  $J = 48$ . Further details on interleaving is found in Data Communication, Networks and Systems, Howard W. Sams & Co., 1987, pp. 343-352. The effect of the  
20 convolutional interleaver is to disperse unreliable channel symbols such that any two symbols in a contiguous sequence of  $I-1$  or fewer symbols are separated by at least  $J+1$  symbols in a deinterleaver output. Equivalently, any two symbols in a contiguous sequence of  $J-1$  symbols are separated by at least  $I+1$  symbols at the deinterleaver output. In other  
25 words, if  $I = 16$  and  $J = 48$ , in a string of 15 symbols, the symbols are transmitted separated by 885  $\mu\text{sec}$ , thus providing time diversity.

The sync channel symbols of the microcell are tied to the pilot signal for the microcell. The pilot signal cycle in the exemplary embodiment is 26.67 msec long, which corresponds to 128 sync channel  
30 code symbols or 32 sync channel information bits. The sync channel symbols are interleaved by a convolutional interleaver which spans 26.67 msec. Thus, when the mobile unit has acquired the pilot signal, it has immediate sync channel interleaver synchronization.

The sync channel symbols are covered by the preassigned Walsh sequence to provide orthogonality in the signal. In the sync channel, one code symbol spans four cover sequences, i.e. one code symbol to four repetitions of the "32 one"-"32 zero" sequence, as illustrated in Figure 6.

5 As illustrated in Figure 6, a single logical "one" represents the occurrence of 32 "one" Walsh chips while a single logical "zero" represents the occurrence of 32 "zero" Walsh chips. Orthogonality in the sync channel is still maintained even though the sync channel symbols are skewed with respect to absolute time depending upon the associated pilot

10 channel because sync channel shifts are integer multiples of the Walsh frame.

The sync channel messages in the exemplary embodiment are variable in length. The length of the message is an integer multiple of 80 msec which corresponds to 3 pilot cycles. Included with the sync channel

15 information bits are cyclic redundancy (CRC) bits for error detection.

As soon as a sync channel message has been correctly received, the mobile unit has the ability to immediately synchronize to either a paging channel or a voice channel. At pilot sync, corresponding to the end of each sync message, a new 40 msec interleaver cycle begins. At that time,

20 the mobile unit starts deinterleaving the first code symbol of either a code repetition, or a  $(c_x, c_{x+1})$  pair, with decoder synchronization achieved. The deinterleaver write address is initialized to 0 and the read address is initialized to J, such that memory deinterleaver synchronization is achieved.

The sync channel messages carry information regarding the state of a 42-bit long PN generator for the voice channel assigned for the communication with the mobile unit. This information is used at the mobile unit digital data receivers to synchronize the corresponding PN

25 generators.

The paging channel information is also encoded with repetition, interleaved and then multiplied by a preassigned Walsh sequence. The resulting sequence is then multiplied by the  $PN_I$  and  $PN_Q$  sequences. The data rate of the paging channel for a particular sector or cell is

30

indicated in an assigned field in the sync channel message. Although the paging channel data rate is variable, it is in the exemplary embodiment fixed for each system at one of the following exemplary data rates: 9.6, 4.8, 2.4 and 1.2 kbps.

5       The data of each voice channel is also encoded with repetition, interleaved, scrambled, multiplied by its assigned Walsh sequence ( $W_i - W_j$ ), and then multiplied by the  $PN_I$  and  $PN_Q$  sequences. The Walsh sequence to be used by a particular channel is assigned by the system controller at call setup time in the same manner as channels are assigned  
10 to calls in the analog FM cellular system. In the exemplary embodiment illustrated herein, up to 61 different Walsh sequences are available for use by the voice channels.

In the exemplary embodiment of the present invention, the voice channel utilizes a variable data rate. The intent in using a variable data  
15 rate is to lower the data rate when there is no voice activity thereby reducing interference generated by this particular voice channel to other users. The vocoder envisioned to provide variable rate data is disclosed in copending U.S. Patent Application "VARIABLE RATE VOCODER" Serial No. \_\_\_\_\_, filed \_\_\_\_\_, also assigned to the  
20 assignee of the present invention. Such a vocoder produces data at four different data rates based on voice activity on a 20 msec frame basis. Exemplary data rates are 9.6 kbps, 4.8 kbps, 2.4 kbps and 1.2 kbps. Although the data rate will vary on a 20 msec basis, the code symbol rate is kept constant by code repetition at 19.2 kbps. Accordingly, the code  
25 symbols are repeated 2, 4 and 8 times for the respective data rates 4.8 kbps, 2.4 kbps and 1.2 kbps.

Since the variable rate scheme is devised to reduce interference, the code symbols at the lower rates will have lower energy. For example, for the exemplary data rates of 9.6 kbps, 4.8 kbps, 2.4 kbps and 1.2 kbps, the  
30 code symbol energy ( $E_s$ ) is respectively  $E_b/2$ ,  $E_b/4$ ,  $E_b/8$  and  $E_b/16$  where  $E_b$  is the information bit energy for the 9.6 kbps transmission rate.

The code symbols are interleaved by a convolutional interleaver such that code symbols with different energy levels will be scrambled by

the operation of the interleaver. In order to keep track of what energy level a code symbol should have a label is attached to each symbol specifying its data rate for scaling purposes. After orthogonal Walsh covering and PN spreading, the quadrature channels are digitally filtered by a Finite Impulse Response (FIR) filter. The FIR filter will receive a signal corresponding to the symbol energy level in order to accomplish energy scaling according to the data rate. The I and Q channels will be scaled by factors of:  $1$ ,  $1/\sqrt{2}$ ,  $1/2$ , or  $1/2\sqrt{2}$ . In one implementation the vocoder would provide a data rate label in the form of a 2-bit number to the FIR filter for controlling the filter scaling coefficient.

In the exemplary embodiment, each voice channel signal is scrambled to provide greater security in cell-to-mobile transmissions. Although such scrambling is not required it does enhance the security in communications. For example, scrambling of the voice channel signals may be accomplished by PN coding the voice channel signals with a PN code determined by the mobile unit address of user ID. Such scrambling may use the PN<sub>U</sub> sequence or encryption scheme as discussed with reference to Figure 3 with respect to the particular receiver for the mobile-to-cell communications. Accordingly, a separate PN generator may be implemented for this function. Although scrambling is discussed with reference to a PN sequence, scrambling may be accomplished by other techniques including those well known in the art.

In addition to voice bits, the forward link voice channel carries power control information. The power control bit rate is in the exemplary embodiment 800 bps. The cell-site receiver which is demodulating the mobile-to-microcell signal from a given mobile, generates the power control information which is inserted in the cell-to-mobile voice channel addressed to that particular mobile. Further details on the power control feature is disclosed in the above identified copending application.

Power control bits are inserted at the output of the convolutional interleaver by means of a technique called code symbol puncturing. In other words, whenever a power control bit needs to be transmitted two

code symbols are replaced by two identical code symbols with polarity given by the power control information. Moreover, power control bits are transmitted at the energy level corresponding to the 9600 bps bit rate.

- 5 An additional constraint imposed on the power control information stream is that the position of the bits must be randomized among mobile-to-cell channels. Otherwise the full energy power control bits would generate spikes of interference at regular intervals, thus diminishing the detectability of such bits.

- 10 The characteristic of interest in the Walsh function is that each of the 64 sequences is perfectly orthogonal to all of the other sequences. As such, any pair of sequences differ in exactly as many bit positions as they agree, i.e. 32 over an interval of 64 symbols. Thus when information is encoded for transmission by the Walsh sequences the receiver will be able to select any one of the Walsh sequences as a desired "carrier" signal.
- 15 Any signal energy encoded onto the other Walsh sequences will be rejected and not result in mutual interference to the desired one Walsh sequence.

- In the exemplary embodiment for the cell-to-mobile link, the sync, paging and voice channels as mentioned previously use convolutional encoding of a constraint length  $K = 9$  and code rate  $r = 1/2$ , that is, two
- 20 encoded symbols are produced and transmitted for every information bit to be transmitted. In addition to the convolutional encoding, convolutional interleaving of symbol data is further employed. It is further envisioned that repetition is also utilized in conjunction with
- 25 the convolutional encoding. At the mobile unit the optimum decoder for this type of code is the soft decision Viterbi algorithm decoder. A standard design can be used for decoding purposes. The resulting decoded information bits are passed to the mobile unit digital baseband equipment.

- 30 CDMA controller 18 has the responsibility for assignment of channel units and vocoders to a particular call. CDMA controller 18 also monitors the progress of the call, quality of the signals and initiates teardown on loss of signal.

In the mobile-to-microcell link, the channel characteristics dictate that the modulation technique be modified. In particular, the use of a pilot carrier as is used in the cell-to-mobile link is no longer feasible. The pilot carrier must be more powerful than a voice carrier in order to  
5 provide a good phase reference for data modulation. With the microcell transmitting many simultaneous voice carriers, a single pilot signal can be shared by all the voice carriers. Therefore, the pilot signal power per voice carrier is quite small.

In the mobile-to-microcell link, however, there is usually only a  
10 single voice carrier per mobile. If a pilot were used, it would require significantly more power than the voice carrier. This situation is clearly not desirable since overall system capacity would be greatly reduced due to the interference caused by the presence of a larger number of high power pilot signals. Therefore, a modulation capable of efficient  
15 demodulation without a pilot signal must be used.

Thus, a form of orthogonal signaling such as binary, quaternary or m-ary signalling should be employed. In the exemplary embodiment, a 64-ary orthogonal signaling technique is employed using Walsh functions. The demodulator for m-ary orthogonal signaling requires  
20 channel coherence only over the duration of transmission of the m-ary symbol. In the exemplary embodiment, this is only two bit times.

The mobile unit transmitted signals are direct sequence spread spectrum signals that are modulated by a PN sequence clocked at a predetermined rate, which in the preferred embodiment is 1.2288 MHz.  
25 This clock rate is chosen to be an integer multiple of the baseband data rate of 9.6 Kbps.

The message encoding and modulation process begins with a convolutional encoder of constraint length  $K = 9$  and code rate  $r = 1/3$ . At a nominal data rate of 9600 bits per second, the encoder produces  
30 28800 binary symbols per second. These are grouped into characters containing 6 symbols each at a rate of 4800 characters per second with there being 64 possible characters. Each character is encoded into a length 64 Walsh sequence containing 64 binary bits or "chips." The 64-ary

Walsh chip rate is 307,200 chips per second in the exemplary embodiment.

5 The Walsh chips are then "covered" or multiplied by a PN sequence running at the rate of 1.2288 MHz. Each mobile unit is assigned a unique PN sequence for this purpose. This PN sequence can either be assigned only for the duration of the call or assigned permanently to the mobile unit. The assigned PN sequence is referred to herein as the user PN sequence. The user PN sequence generator runs at a clock rate of 1.2288 MHz and so as to produce four PN chips for every Walsh chip.

10 Finally, a pair of short, length 32768, PN sequences are generated. In the exemplary embodiment, the same sequences are used as for the cell-to-mobile link. The user PN sequence covered Walsh chip sequence is then covered or multiplied by each of the two short PN sequences. The two resulting sequences then bi-phase modulate a quadrature pair of  
15 sinusoids and are summed into a single signal. The resulting signal is then bandpass filtered, translated to the final RF frequency, amplified, filtered and radiated by the antenna of the mobile unit. As was discussed with reference to the cell-to-mobile signal, the ordering of the filtering, amplification, translation and modulation operations may be  
20 interchanged.

In an alternative embodiment, two different phases of the user PN code might be produced and used to modulate the two carrier phases of the quadrature waveform, dispensing with the need for using the length 32768 sequences. In yet another alternative, the mobile-to-cell  
25 link might utilize only bi-phase modulation, also dispensing with the need for the short sequences.

The microcell receiver for each signal produces the short PN sequences and the user PN sequence for each active mobile signal being received. The receiver correlates the received signal energy with each of  
30 the coded waveforms in separate correlators. Each of the correlator outputs is then separately processed to demodulate the 64-ary encoding and the convolutional coding using a Fast Hadamard Transform processor and a Viterbi algorithm decoder.



Figure 5 illustrates in block diagram form an exemplary mobile unit CDMA telephone set. The mobile unit CDMA telephone set includes an antenna 200 which is coupled through diplexer 202 to analog receiver 204 and transmit power amplifier 206. Antenna 200 and diplexer 202 are of standard design and permit simultaneous transmission and reception through a single antenna. Antenna 200 collects transmitted signals and provides them through diplexer 202 to analog receiver 204.

Receiver 204 receives the RF frequency signals from diplexer 202 which are typically in the 850 MHz frequency band for amplification and frequency downconversion to an IF frequency. This translation process is accomplished using a frequency synthesizer of standard design which permits the receiver to be tuned to any of the frequencies within the receive frequency band of the overall cellular telephone frequency band. The signals are also filtered and digitized for providing to digital data receivers 210 and 212 along with searcher receiver 214. Further details of an exemplary embodiment of receivers 204, 210, 212 and 214 are illustrated in copending application Serial No. 07/543,496.

Receiver 204 also performs a power control function for adjusting the transmit power of the mobile unit. Receiver 204 generates an analog power control signal that is provided to transmit power control circuitry 208.

In Figure 5, the digitized signal output from receiver 204 is provided to digital data receivers 210 and 212 and to searcher receiver 214. It should be understood that an inexpensive, low performance mobile unit might have only a single data receiver while higher performance units may have two or more to allow diversity reception.

The digitized IF signal may contain the signals of many on-going calls together with the pilot carriers transmitted by the current cell-site and all neighboring cell-sites. The function of the receivers 210 and 212 are to correlate the IF samples with the proper PN sequence. This correlation process provides a property that is well-known in the art as "processing gain" which enhances the signal-to-interference ratio of a

signal matching the proper PN sequence while not enhancing other signals. Correlation output is then synchronously detected using the pilot carrier from the closest cell-site as a carrier phase reference. The result of this detection process is a sequence of encoded data symbols.

5       A property of the PN sequence as used in the present invention is that discrimination is provided against multipath signals. When the signal arrives at the mobile receiver after passing through more than one path, there will be a difference in the reception time of the signal. This reception time difference corresponds to the difference in distance  
10       divided by the velocity of propagation. If this time difference exceeds one microsecond, then the correlation process will discriminate between the paths. The receiver can choose whether to track and receive the earlier or later path. If two receivers are provided, such as receivers 210 and 212, then two independent paths can be tracked and processed in  
15       parallel.

Searcher receiver 214, under control of control processor 216 is for continuously scanning the time domain around the nominal time of a received pilot signal of the microcell for other multi-path pilot signals. Receiver 214 will measure the strength of any reception of a desired  
20       waveform at times other than the nominal time. Receiver 214 compares signal strength in the received signals. Receiver 214 provides a signal strength signal to control processor 214 indicative of the strongest signals. Processor 216 provides control signals to data receivers 210 and 212 for each to process a different one of the strongest signals.

25       Control processor 216 also includes a PN generator which generates the user PN sequence in response to an input mobile unit address or user ID. The PN sequence output from the PN generator is provided to diversity combiner and decoder circuitry 218. Since the microcell-to-mobile signal is scrambled with the mobile user address PN  
30       sequence, the output from the PN generator is used in descrambling the cell-site transmitted signal intended for this mobile user similar to that as in the microcell receiver. The PN generator specifically provides the output PN sequence to deinterleaver and decoder circuitry where it is

used to descramble the scrambled user data. Although scrambling is discussed with reference to a PN sequence, it is envisioned that other scrambling techniques including those well known in the art may be utilized.

- 5           The outputs of receivers 210 and 212 are thus provided to diversity combiner and decoder circuitry 218. The diversity combiner circuitry contained within circuitry 218 simply adjusts the timing of the two streams of received symbols into alignment and adds them together. This addition process may be proceeded by multiplying the two streams  
10 by a number corresponding to the relative signal strengths of the two streams. This operation can be considered a maximal ratio diversity combiner. The resulting combined signal stream is then decoded using a forward error detection (FEC) decoder also contained within circuitry 218. The usual digital baseband equipment is a digital vocoder system. The  
15 CDMA system is designed to accommodate a variety of different vocoder designs.

- Baseband circuitry 220 typically includes a digital vocoder (not shown) which may be a variable rate type as disclosed in the previously mentioned copending patent application. Baseband circuitry 220 further  
20 serves as an interface with a handset or any other type of peripheral device. Baseband circuitry 220 accommodates a variety of different vocoder designs. Baseband circuitry 220 provides output information signals to the user in accordance with the information provided thereto from circuitry 218.

- 25           In the mobile-to-microcell link, user analog voice signals are typically provided through a handset as an input to baseband circuitry 220. Baseband circuitry 220 includes an analog to digital (A/D) converter (not shown) which converts the analog signal to digital form. The digital signal is provided to the digital vocoder where it is encoded. The  
30 vocoder output is provided to a forward error correction (FEC) encoding circuit (not shown) for error correction. In the exemplary embodiment the error correction encoding implemented is of a convolutional

encoding scheme. The digitized encoded signal is output from baseband circuitry 220 to transmit modulator 222 .

Transmit modulator 222 first Walsh encodes the transmit data and then modulates the encoded signal on a PN carrier signal whose PN sequence is chosen according to the assigned address function for the call. The PN sequence is determined by control processor 216 from call setup information that is transmitted by the cell-site and decoded by receivers 210 and 212, and control processor 216. In the alternative, control processor 216 may determine the PN sequence through prearrangement with the cell-site. Control processor 216 provides the PN sequence information to transmit modulator 222 and to receivers 210 and 212 for call decoding.

The output of transmit modulator 222 is provided to transmit power control circuitry 208. Signal transmission power is controlled by the analog power control signal provided from receiver 204. Control bits transmitted by the microcell in the form power adjustment command are processed by data receivers 210 and 212. The power adjustment command is used by control processor 216 in setting the power level in mobile unit transmission. In response to this command, control processor 216 generates a digital power control signal that is provided to circuitry 208. Further information on the relationship of receivers 210, 212 and 214, control processor 216 and transmit power control 208 with respect to power control is further described in the above-mentioned copending patent application.

Transmit power control circuitry 208 outputs the power controlled modulated signal to transmit power amplifier circuitry 206. Circuitry 206 amplifies and converts the IF signal to an RF frequency by mixing with a frequency synthesizer output signal which tunes the signal to the proper output frequency. Circuitry 206 includes an amplifier which amplifies the power to a final output level. The intended transmission signal is output from circuitry 206 to diplexer 202. Diplexer 202 couples the signal to antenna 200 for transmission to the microcell.

With respect to transmission by the mobile unit, the mobile user analog voice signal is first passed through a digital vocoder. The vocoder output is then, in sequence, convolutional forward error correction (FEC) encoded, 64-ary orthogonal sequence encoded and modulated on a  
5 PN carrier signal. The 64-ary orthogonal sequence is generated by a Walsh function encoder. The encoder is controlled by collecting six successive binary symbol outputs from the convolutional FEC encoder. The six binary collectively determine which of the 64 possible Walsh sequences will be transmitted. The Walsh sequence is 64 bits long. Thus,  
10 the Walsh "chip" rate must be  $9600 \cdot 3 \cdot (1/6) \cdot 64 = 307200$  Hz for a 9600 bps data transmission rate.

In the mobile-to-microcell link, a common short PN sequence is used for all voice carriers in the system, while user address encoding is done using the user PN sequence generator. The user PN sequence is  
15 uniquely assigned to the mobile for at least the duration of the call. The user PN sequence is exclusive-OR'ed with the common PN sequences, which are length 32768 augmented maximal linear shift register sequences. The resulting binary signals then each bi-phase modulate a quadrature carrier, are summed to form a composite signal, are bandpass  
20 filtered, and translated to an IF frequency output. In the exemplary embodiment, a portion of the filtering process is actually carried out by a finite impulse response (FIR) digital filter operating on the binary sequence output.

The modulator output is then power controlled by signals from  
25 the digital control processor and the analog receiver, converted to the RF frequency of operation by mixing with a frequency synthesizer which tunes the signal to proper output frequency, and then amplified to the final output level. The transmit signal is then passed on to the diplexer and the antenna.

30 In mobile unit transmit modulator 222, data is provided in digital form from the user digital baseband circuitry to an encoder where in the exemplary embodiment is convolutionally encoded, block encoded and Walsh encoded.

Transmit modulator further includes a PN generator which receives the mobile unit address as an input in determining the output PN sequence. This PN generator generates the user specific 42-bit sequence as was discussed to the microcell. A further attribute of this PN generator that is common to all user PN generators and not previously discussed is the use of a masking technique in generating the output user PN sequence. For example, a 42-bit mask is provided for that user with each bit of the 42-bit mask exclusive-OR'ed with a bit output from each register of the series of shift register that form the PN generator. The results of the mask and shift register bit exclusive-OR operation are then exclusive-OR'ed together to form the PN generator output that is used as the user PN sequence.

Transmit modulator 222 includes PN generators which generate the  $PN_I$  and  $PN_Q$  sequences which all mobile units use. These PN sequences are in the exemplary embodiment the zero-shift used in the microcell-to-mobile communications.

In the exemplary embodiment, the mobile-to-cell link uses rate  $r = 1/3$  convolutional code with constraint length  $K = 9$ . The generators for the code are  $G_1 = 557$  (octal),  $G_2 = 663$  (octal), and  $G_3 = 711$  (octal). Similar to the cell-to-mobile link, code repetition is used to accommodate the four different data rates that the vocoder produces on a 20 msec frame basis. Unlike the microcell-to-mobile link, the repeated code symbols are not transmitted over the air at lower energy levels, rather only one code symbol of a repetition group is transmitted at the nominal power level. In conclusion, the code repetition in the exemplary embodiment is used merely as an expedient to fit the variable data rate scheme in the interleaving and modulation structure as it will be shown in the following paragraphs.

A block interleaver spanning 20 msec, exactly one vocoder frame, is used in the mobile-to-cell link. The number of code symbols in 20 msec, assuming a data rate of 9600 bps and a code rate  $r=1/3$ , is 576. The  $N$  and  $B$  parameters,  $N$  is equal to the number of rows and  $B$  to the number of columns of the interleaver array are 32 and 18, respectively. The code

symbols are written into the interleaver memory array by rows and read out by columns.

The modulation format is 64-ary orthogonal signalling. In other words, interleaved code symbols are grouped into groups of six to select one out of 64 orthogonal waveforms. The 64 time orthogonal waveforms are the same Walsh functions used as cover sequences in the cell-to-mobile link.

The data modulation time interval is equal to 208.33  $\mu$ sec, and is referred to as a Walsh symbol interval. At 9600 bps, 208.33  $\mu$ sec corresponds to 2 information bits and equivalently to 6 code symbols at a code symbol rate equal to 28800 sps. The Walsh symbol interval is subdivided into 64 equal length time intervals, referred to as Walsh chips, each lasting  $208.33 / 64 = 3.25 \mu$ sec. The Walsh chip rate is then  $1/3.25 \mu$ sec = 307.2 kHz. Since the PN spreading rate is symmetric in the two links, i.e. 1.2288 MHz, there are exactly 4 PN chips per Walsh chip.

A total of three PN generators are used in the mobile-to-cell link path. The user specific 42-bit PN generator and the pair of 15-bit I and Q channel PN generators. Following the user specific spreading operation, the signal is QPSK spread as it was done in the cell-to-mobile link. Unlike the cell-to-mobile link, where each sector or cell was identified by unique sequences of length  $2^{15}$ , here all mobile units use the same I and Q PN sequences. These PN sequences are the zero-shift sequences used in the cell-to-mobile link, also referred to as the pilot sequences.

Code repetition and energy scaling are used in the microcell-to-mobile link to accommodate the variable rates produced by the vocoder. The mobile-to-microcell link uses a different scheme based on a burst transmission.

The vocoder produces four different data rates, i.e. 9600, 4800, 2400, and 1200 bps, on a 20 msec frame basis as in the cell-to-mobile link. The information bits are encoded by the rate  $r = 1/3$  convolutional encoder and code symbols are repeated 2, 4, and 8 times at the three lower data rates. Thus, the code symbol rate is kept constant at 28800 sps. Following the encoder, the code symbols are interleaved by the block interleaver

which spans exactly one vocoder frame or 20 msec. A total of 576 code symbols are generated every 20 msec by the convolutional encoder, some of which might be repeated symbols.

- A vocoder frame of 20 msec is subdivided into 16 slots each
- 5 lasting 1.25 msec. The numerology of the mobile-to-cell link is such that in each slot there are 36 code symbols at the 28800 sps rate or equivalently 6 Walsh symbols at the 4800 sps rate. At the  $1/2$  rate, i.e. 4800 bps, the slots are grouped into 8 groups each comprising 2 slots. At the  $1/4$  rate, i.e. 2400 bps, the slots are grouped into 4 groups each comprising 4 slots,
- 10 and finally at the  $1/8$  rate, i.e. 1200 bps, the slots are grouped into 2 groups each comprising 8 slots.

- The mobile unit in order to originate a call must be provided with signaling attributes in order to complete a call to another system user via a cell-site. In the mobile-to-microcell link the envisioned access
- 15 technique is the slotted ALOHA. An exemplary transmission bit rate on the reverse channel is 4800 bps. An access channel packet is comprised of a preamble followed by the information.

- The preamble length is in the exemplary embodiment an integer multiple of 20 msec frames and is a sector/cell parameter which the
- 20 mobile receives in one of the paging channel messages. Since the cell receivers use the preambles to resolve propagation delays this scheme allows the preamble length to vary based on the cell radius. The users PN code for the access channel is either prearranged or transmitted to the mobile units on the paging channel.

- 25 The modulation is fixed and constant for the duration of the preamble. The orthogonal waveform used in the preamble is  $W_0$ , i.e. the all zero Walsh function. Notice that an all zero pattern at the input of the convolutional encoder generates the desired waveform  $W_0$ .

- An access channel data packet may consist of one or at most two 20 msec frames. The coding, interleaving, and modulation of the access channel is exactly the same as for a voice channel at the 4800 bps rate, except that the transmission is not bursty in nature and all code symbols transmitted. In an exemplary embodiment, the sector/cell
- 30



requires the mobile units to transmit a 40 msec preamble and the access channel message type requires one data frame. Let  $N_p$  be the number of preamble frames where  $k$  is the number of 20 msec elapsed from a predefined time origin. Then mobiles are allowed to initiate transmission on the access channel only when the equation:  $(k, N_p+2) = 0$  is true.

With respect to other communications applications it may be desirable to rearrange the various elements of the error correction coding, the orthogonal sequence coding and the PN coding to better fit the application.

The previous description of the preferred embodiments is provided to enable any person skilled in the art to make or use the present invention. The various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without the use of the inventive faculty. Thus, the present invention is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

20

**WE CLAIM:**

## CLAIMS

1. In a code division multiple access (CDMA) communication  
2 system having a base station for communicating information signals  
with system users using CDMA communication signals, an antenna  
4 system comprising:  
a plurality of spaced apart antennas;  
6 signal distribution means for coupling CDMA communication  
signals between a base station and said antennas; and  
8 delay means operatively coupled to said antennas and said signal  
distribution means for providing a predetermined delay in said CDMA  
10 communication signals coupled between a base station and said  
antennas.
2. The system of Claim 1 wherein said signal distribution  
2 means comprises transmission cabling serially interconnecting said  
antennas and interconnecting a first one of said antennas to a base  
4 station.
3. The system of Claim 2 wherein said delay means comprises  
2 a plurality of delay elements disposed in said cabling between adjacent  
coupled ones of said antennas, each delay element providing a delay on  
4 an order of at least one chip time of a CDMA signal chip.
4. The system of Claim 1 wherein said antennas each have a  
2 predetermined antenna pattern with said antennas positioned with  
overlapping patterns.
5. The system of Claim 5 wherein said antennas are  
2 positioned with substantially overlapping patterns.

6. The system of Claim 1 wherein said signal distribution  
2 means comprises:  
a local antenna electrically coupled to a base station; and  
4 a plurality of remote antennas electromagnetically coupled to said  
local antenna, with each remote antenna coupled to a corresponding one  
6 of said antennas.

7. The system of Claim 6 wherein said delay means comprises  
2 a plurality of delay elements each disposed between corresponding ones  
of said antennas and remote antennas, each delay element providing a  
4 delay on an order of at least one chip time of a CDMA signal chip.

8. The system of Claim 6 wherein said antennas each have a  
2 predetermined antenna pattern with said antennas positioned with  
overlapping patterns.

9. The system of Claim 6 wherein said antennas are  
2 positioned with substantially overlapping patterns.

10. In a code division multiple access (CDMA) cellular  
2 telephone system for facilitating communications between users of said  
CDMA cellular telephone system, and between users of said CDMA  
4 cellular telephone system and other system users, a base station for  
communicating information with at least one mobile terminal using  
6 CDMA communication signal comprising:  
a private branch exchange (PBX);  
8 a CDMA communications terminal for receiving, converting and  
transmitting input information signals from said PBX intended for a  
10 recipient mobile terminal into CDMA communication signals, and for  
receiving and converting CDMA communication signals from a  
12 transmitting mobile terminal into output information signals for output  
to said PBX, said CDMA communications terminal having antenna  
14 means for radiating and collecting said CDMA communication signals

with said antenna means providing multiple radiations and collections  
16 of a same CDMA communication signal each with a different  
predetermined time offset with respect to one another.

11. The system of Claim 10 wherein said antenna means  
2 comprises:  
a plurality of spaced apart antennas;  
4 signal distribution means for coupling CDMA communication  
signals between said CDMA communications terminal and said  
6 antennas; and  
delay means operatively coupled to said antennas and said signal  
8 distribution means for providing a predetermined delay in said CDMA  
communication signals coupled between said CDMA communications  
10 terminal and said antennas.




FIGURE 1




FIGURE 2




FIGURE 3




FIGURE 4

4/4




FIGURE 5



# INTERNATIONAL SEARCH REPORT

International Application No. **PCT/US91/09295**

<b>I. CLASSIFICATION OF SUBJECT MATTER</b> (If several classification symbols apply, indicate all) *		
According to International Patent Classification (IPC) or to both National Classification and IPC IPC (5): <b>H04J 13/00</b> U.S.Cl.: <b>370/18</b>		
<b>II. FIELDS SEARCHED</b>		
Minimum Documentation Searched †		
Classification System	Classification Symbols	
U.S.Cl.	370/93,18,60 375/1	
Documentation Searched other than Minimum Documentation to the Extent that such Documents are Included in the Fields Searched ‡		
<b>III. DOCUMENTS CONSIDERED TO BE RELEVANT</b> §		
Category *	Citation of Document, † with indication, where appropriate, of the relevant passages ‡	Relevant to Claim No. 12
A,P	US, A, 4,984,247 published 08 JANUARY 1991 See Abstract.	10, 11
A	US, A, 4,761,778 (HUI) 02 August 1988 See Abstract.	1-9
<div style="display: flex; justify-content: space-between;"> <div style="width: 45%;"> <p>* Special categories of cited documents: †</p> <p>"A" document defining the general state of the art which is not considered to be of particular relevance</p> <p>"E" earlier document but published on or after the international filing date</p> <p>"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)</p> <p>"O" document referring to an oral disclosure, use, exhibition or other means</p> <p>"P" document published prior to the international filing date but later than the priority date claimed</p> </div> <div style="width: 45%;"> <p>"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention</p> <p>"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step</p> <p>"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.</p> <p>"&amp;" document member of the same patent family</p> </div> </div>		
<b>IV. CERTIFICATION</b>		
Date of the Actual Completion of the International Search	Date of Mailing of this International Search Report	
21 February 1992	<b>08 APR 1992</b>	
International Searching Authority	Signature of Authorized Official	
ISA/US	<b>INTERNATIONAL DIVISION</b> Temesghen Samuel <i>Nguyen</i>	